

DEXXO PRO 800/1000 3S io

GARAGE DOOR MOTORIZATION




Programming interface

Application area*



* For DEXXO Pro 1000 3S only. Note: some of these doors may be impossible to motorize. Consult Somfy's technical services. More information page 122.

General wiring diagram





Reliable and robust motorization for every installation configuration

Very easy to use

- Starts working in less than 90 seconds
- All settings are pre-programmed
- Intuitive easy and safe programming thanks to the LCD screen

Extensive scope for customizing the installation

- 15 adjustable parameter settings
- A wide range of safety and comfort accessories can be connected
- A backup battery can be incorporated in the motor unit to cater for power cuts
- Can be connected to a separate lighting unit rated up to 500 W

Maintenance aids

- Real-time display of motor operating status
- Real-time display of fault and failure codes
- Access to maintenance data: opening and closing counters, fault logs, etc.

Garage door security features

- Burglar-proof lock

Robustness that stands the test of time

- 5-year warranty


Comprehensive range of transmission systems

- Chain, belt, high-performance chain drives

io homecontrol® technology

- Compatible with all equipment in the Somfy io range
- Feedback from all two-way io remote controls
- Remote operation and control with TaHoma® and Connexoon

General overall size



Technical characteristics

	Dexxo Pro 800 3S io	Dexxo Pro 1000 3S io
Mains power supply	230 V - 50/60 Hz	
Motor voltage	24 Vdc	
Maximum power consumption in operation	600 W (with 500 W lighting)	
Maximum power consumption on standby	7 W	
Traction force	800 N	1000 N
Maximum speed	21 cm/s	
Operating temperature	-20°C / +60°C	
io radio frequency	868 - 870 MHz	
Number of remote controls	One-way (Keygo io,...): 9 channels maximum - Two-way (Keytis io,...): unlimited	